



SPA 5500Public Address System 500W Mixer Amplifier

Siera manufactures reliable and affordable solutions in Electronic Security, CCTV, Access Control, Intercommunications, Professional Audio and Automation.

Featured specifications

- · Commercial & industrial range BGM & paging amplifier.
- · 3 microphone inputs and 2 line inputs.
- Mic1 on front panel by phone jack, mic2-3 on rear panel by phone jack.
- · Line 1-2 inputs on rear panel by RCA.
- · Volume control on front panel with bass and treble tone control.
- · Overload, short circuit and high temp protection.
- · With cooling fan.

Rated Power Output:	500W
Inputs:	Mic1-3: 600 ohms(Ω) 5-8 mV, unbalanced
·	Line1-2: $10k$ ohms(Ω) $150-470$ mV, unbalanced
Frequency Response:	60Hz-15kHz
S/N Ratio:	Line: 85 dB , MIC: >72 dB
THD:	<0.5% at 1kHz, 1/3 rated power
Protection:	High temp, short circuit, overload protection
Power Consumption:	650W
Power Supply:	AC 110V / AC220V - 50-60Hz
Dimension:	484(W)×366(D)×88(H)mm
Net weight:	16.5kg
Gross weight:	17ka

